

Features

Drives arbitrary current waveforms into laser diodes
 CW, pulsed, modulated or mixed
 Excellent dynamic performance
 Two analog inputs
 Small dimensions


Specification

Diode current	0 ... 100 A
Diode voltage	0 ... 5 V
Output power	500 W max
Power dissipation	150 W max allowed
Supply voltage	3 V ... 6 V
Supply current	101 A max
Rise time	9 μ s
Fall time	11. μ s
Bandwidth	50 KHz

Inputs

Diode current set point 1	0 ... 500 mV (50 Ohm input)
Diode current set point 2	0 ... 5 V (high impedance input)
Enable	TTL
Reset	TTL

Outputs

Diode current monitor	0 ... 50 mV (into 50 Ohm)
Temperature	0 ... 4 V for 0 ... 80°C
Ready	TTL
Excess Temperature	TTL

General specifications

Ambient temperature	0 ... +45 °C
Cooling	Required
Dimensions	95 x 61 x 20 mm
Weight	275 g
Ordering Code	10100444

Description

The medium speed current modulator MSM 100-06 is a linear modulator which is well suited for driving arbitrary current waveforms into laser diodes.

Current waveforms can be CW, pulsed, modulated or mixed with a bandwidth of up to 50 KHz and currents up to 100 A.

The MSM 100-06 is small and compact and it is designed for mounting it with low inductance directly at laser diodes or for integrating it in laser diode modules.

The MSM 100-06 has two analogue inputs for the current setpoint, a 50 Ohm input with a bandwidth of 50 KHz and a high impedance input with a bandwidth of 50 KHz. Both inputs cover the full current range.

Additionally there is a 10 turns potentiometer for generating a CW-current (bias current).

All set points are added and build the effective current set point.

For detailed information see operating manual or visit our website.